

# SYSTEMS EXAM

Spring 2022

90 minutes

Check which problems you are submitting:

#1

#2

#3

How many pages total? \_\_\_\_\_

Please do not write on the back of any pages.

\_\_\_\_\_  
(print name)

\_\_\_\_\_  
(signature)

\_\_\_\_\_  
(NetId)



b) (10pts) Assume memory has **8 pages** and there are **4 page frames**. We have a page reference string of **2,6,5,7** to fill the first 4 frames. Complete the tables below by adding **three more page references** that will result in **LRU** having **fewer** page faults than **FIFO**.

**LRU**

<b>pages</b>	<b>2</b>	<b>6</b>	<b>5</b>	<b>7</b>	<b>?</b>	<b>?</b>	<b>?</b>
<b>Frame 0</b>	<b>2</b>	<b>2</b>	<b>2</b>	<b>2</b>			
<b>Frame 1</b>		<b>6</b>	<b>6</b>	<b>6</b>			
<b>Frame 2</b>			<b>5</b>	<b>5</b>			
<b>Frame 3</b>				<b>7</b>			

- e) (4pts) What would be the **implementation** of a **block** and **wait semaphore** and how is the **value** of any semaphore modified?
- f) (4pts) A computer system has a **36-bit virtual address space** with a **page size of 8K**, and **4 bytes per page table entry**. How many **pages** are in the virtual address space? What is the **maximum size** of addressable **physical** memory in this system?